

PUBLIC ADDRESS / PROGRAMMERS / PROGRAMMERS/TIMERS

MP-121P

WEEKLY PROGRAMMER



DESCRIPTION

USB/SD programmer/player

Weekly programming of MP3 file playback: bells, advertisements, background music, etc.

Especially suitable for schools, offices, shops, churches, etc.

Direct playback of 9 messages via remote push button.

TECHNICAL CHARACTERISTICS

| | |
|------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| FEATURES | <p>Weekly programmer.</p> <p>USB/SD player.</p> <p>LCD display.</p> <p>Priority paging.</p> <p>9 messages, individually selectable via direct access buttons or contact closure.</p> |
| RESPONSE | 50-18,000 Hz ± 3 dB |
| DISTORTION | Harmonic: < 0.5% at 1 kHz |
| INPUTS | <p>2 balanced mics/lines, combo (XLR and 6.3 mm jack) 600 Ohm 4 mV RMS and 47,000 Ohm 360 mV RMS, switchable</p> <p>2 aux, 2 x RCA 10,000 Ohm 120 mV RMS</p> |
| OUTPUTS | <p>1 master, 2 x RCA and 2 x XLR 600 Ohm 1 V mono/stereo selectable</p> <p>1 rec out, 2 x RCA</p> |



Expand product information on:
<https://fonestar.com/es/MP-121P>

| | |
|--------------|---------------------------------------------------------------------------------------------------|
| CONTROLS | Tone: bass and treble Balance Volume: input 1 and 2, aux 3 and 4, USB/SD and general volume |
| PRIORITY | Mic. 1 through signal level, selectable |
| POWER SUPPLY | 230/115 V AC, 9 W |
| DIMENSIONS | 483 x 89 x 310 mm depth. 2 U 19" rack |
| WEIGHT | 4.5 kg |



Expand product information on:
<https://fonestar.com/es/MP-121P>